Micergy

Solar Home System Pay-As-You-Go SHS | MP1

Pay-As-You-Go refers to a business model that allows users to pay for their product visa embedded consumer financing. A Paygo company will typically offer a solar product (predominantly solar home systems and multi-light pico devices) for which a customer makes a down payment, followed by regular payments for a term ranging from six months to eight years. Payments are usually made via mobile money, though there are alternative methods that include scratch cards, mobile airtime and cash. Micergy MP1 designed with **built-in metering and monitoring technology** allow the end-users to enjoy the advanced feature of the solar home system by paying in installment, rather than making full payment upfront. Besides, advanced encryption technology was adopted to minimize the risk of illegal tamper and theft to reduce the default rate for PAYG operators.



GENERAL SPECIFICATIONS	MP1
Input Ports	1 x 9V/3A DC Input Port
	1 x 9V/3A AC Adaptor Input Port
Output Ports	1 x 5V/1A USB 2.0 Type A Output Port
	4 x 6V/0.4A Encrytped Lamp Port, Automatic detection
	1 x 6V/0.4A Encrytped Custom Port for LED Torch and FM Radio
Battery	Lithium Iron Phosphate, 26650 Type
	Battery Norminal Voltage, 6.4V
	Battery Capacity, 6600mAh
	Long Lifecycle @ High Charge & Discharge Rate
	Over Charge Protection for Individual Cells and Sets of Parallel-Connected Cells
Solar Panel	9V/15Wp @ STC
	6m Charging Cable
	Aluminum Frame
	Dimension: 350*318*18mm
LED Lamp (150 lumen)	Lumen Efficacy: 110lm/w @ High Setting
	Dimmable with 3 Brightness Level
	Encrypted Powering
	10m Cable
PAY-AS-YOU-GO	
LCD Display	128*64 dot matrix LCD display with backlight
	- Battery level: 1% to 100%
	- Remaining credit days: >N Days
	- Remaining battery usage time: >N Hours (Automatically calculated as per load plugged)
	- Device information, software version, manufacturer information, Fault warning information
Keypad	4 x 3 capacitive touch keypad with buzzer sound
	- High sensitivity, stability and reliability
	- Buzzer sound feedback when touching the keypad
	- Remaining battery usage time: >N Hours (Automatically calculated as per load plugged)
	- Buzzer sound remind when the battery level is low
PAYG Compatibility	Software Agnostic PAYG Hardware, Already Compatible with 3rd Party PAYG Software:
	- Angaza
	- Solaris
	- Раудее
	* Micergy can do compatible integration with any customized PAYG software
OPTIONAL ACCESSORIES	
FM Radio	FM 76-108MHz, 50cm Telescopic Rod Antenna, 3.7V/2000mAh, Encrypted Charging
LED Torch	100 lumen, 3-level Dimmable, 3.7V/2000mAh, Encrypted Charging



Micergy Company Limited

Address: Building No.88, Liangtouwei Road, Qingxi Town, Dongguan City, Guangdong Province, China Email: info@micergy.com ; Website: www.micergy.com



The Micergy word mark and logo are registered trade marks owned by Micergy Company Limited and its Subsidiaries. All features, functionality and other product specifications are subject to change without notice or obligation. © 2024 Micergy Co., Ltd. All rights reserved.